PIONEER®
The Art of Entertainment

Service Manual



ORDER NO.
ARP2155

STEREO PREAMPLIFIER
EXCLUSIVE C7

- **This manual is applicable to the EXCLUSIVE C7/MEWZ type.**
- **Ce manuel pour le service comprend les explications de réglage en français.**
- **Este manual de servicio trata del método ajuste escrito en español.**

CONTENTS

PIONEER ELECTRONIC CORPORATION 4-1, Meguro 1-Chome, Meguro-ku, Tokyo 153, Japan
PIONEER ELECTRONICS SERVICE INC. P.O. Box 1760, Long Beach, California 90801 U.S.A.
PIONEER ELECTRONICS OF CANADA, INC. 505 Cochrane Drive, Markham, Ontario L3R 8E3 Canada
PIONEER ELECTRONIC [EUROPE] N.V. Keetberglaan 1, 9120 Beveren, Belgium
PIONEER ELECTRONICS AUSTRALIA PTY. LTD. 178-184 Boundary Road, Braeside, Victoria 3195, Australia TEL: [03] 580-9911

FV JUNE 1991 Printed in Japan

1. EXPLODED VIEWS, PACKING AND PARTS LIST

NOTES:

- *Parts without part number cannot be supplied.*
- *Parts marked by "◉" are not always kept in stock. Their delivery time may be longer than usual or they may be unavailable.*
- *The ⚠ mark found on some component parts indicates the importance of the safety factor of the part. Therefore, when replacing, be sure to use parts of indetical designation.*

1.1 EXPLODED VIEWS, PACKING AND PARTS LIST

Mark	No.	Description	Part No.
	1.	KNOB LARGE	AAB1197
	2.	KNOB SMALL	AAB1198
	3.	POWER KNOB HOLDER	AAC1039
	4.	POWER KNOB MOULD	AAC1040
	5.	POWER KNOB CAP	AAD1889
	6.	DOOR	AAH1047
	7.	SEALING PANEL	AAH1049
	8.	GOLD MOLE	AAH1051
	9.	STAND-BY DISPLAY	AAK2051
	10.	POWER LENS	AAK2052
	11.	NAME PLATE	
	12.	SCREW	ABA-298
	13.	SCREW (STEEL)	ABA1006
	14.	SCREW (STEEL)	ABA1011
	15.	SCREW	ABA1009
	16.	SCREW (STEEL)	ABA1014
	17.	SCREW 3×14	ABA1024
	18.	SCREW (STEEL)	ABA1048
	19.	SCREW (STEEL)	ABA1053
	20.	SCREW	ABA1101
	21.	WASHER (COPPER)	ABE1001
	22.	BUSH	ABF1012
	23.	WASHER	ABF1020
	24.	COILED SPRING	ABH1067
	25.	LOCK SPRING	ABK1014
	26.	WASHER	ABE1002
⚠	27.	AC POWER CORD	ADG1093
	28.	LAMP HOLDER	
	29.	DAMP RUBBER	
	30.	DAMPER A	
	31.	DAMPER B	
	32.	DAMPER C	
	33.	DAMPER D	
	34.	DAMPER E	
	35.	DAMPER F	
	36.	DAMPER G	
	37.	DAMPER H	
	38.	DAMPER I	
	39.	DAMP BUSH	
	40.	GROMMET	
	41.	BINDER	
	42.	WIRE CLIP A	
	43.	WIRE CLIP B	
	44.	PAD	
	45.	DAMPING FELT A	
	46.	DAMPING FELT B	
	47.	DAMPING FELT C	
	48.	PAD(F/R)	AHA1435
	49.	PACKING CASE	AHD2088
	50.	PACKING SHEET	
	51.	TERMINAL (2P)	
	52.	GROUND TERMINAL	AKE-045
	53.	SOCKET (3P)	
	54.	FUSE HOLDER	AKR1001
	55.	GEAR MOLD L	
	56.	GEAR MOLD R	
	57.	AC CORD MOLD	
	58.	PIN JACK PLATE	
	59.	CHASSIS	
	60.	FRONT PANEL	ANB1475
	61.	REAR PANEL	
	62.	PANEL STAY	
	63.	FRONT SUB STAY	
	64.	SIDE REAR STAY L	
	65.	SIDE REAR STAY R	
	66.	SIDE PLATE L	ANE1263
	67.	SIDE PLATE R	ANE1264
	68.	TOP PLATE A	ANE1299
	69.	TOP PLATE B	ANE1300
	70.	BOTTOM PLATE	
	71.	AC CORD COVER	
	72.	PCB HOLDER A	
	73.	PCB HOLDER B	
	74.	PCB HOLDER C	
	75.	REAR P.C.B HOLDER -A	
	76.	REAR P.C.B HOLDER -B	
	77.	REAR P.C.B HOLDER -C	
	78.	REAR P.C.B HOLDER -D	
	79.	REAR P.C.B HOLDER -E	
	80.	REAR P.C.B HOLDER -F	
	81.	VOLUME STAY	
	82.	DOOR STAY L	
	83.	DOOR STAY R	
	84.	REAR STAY	

Mark	No.	Description	Part No.
	85.	LAMP STAY -B	
	86.	• • • • •	
	87.	SHIELD PLATE A	
	88.	SHIELD PLATE B	
	89.	SHIELD PLATE C	
	90.	P.C.B SHIELD STAND	
	91.	DIODE SHIELD PLATE	
	92.	TRANS. SHIELD PLATE	
	93.	AC CORD SPACER	
	94.	JOINT	
	95.	LEG ASS'Y	
	96.	OPE.INSTRUCTIONS (G)	ARC1231
	97.	DAMPER	AXA1009
	98.	STEPPING MOTOR	AXM1010
	99.	SCREW	BBT30P100FCC
	100.	SCREW	BMZ30P140FCC
	101.	SCREW	CBZ30P060FCC
	102.	SCREW	CBZ30P080FCC
	103.	SCREW	CCZ30P060FCC
	104.	NUT	NB23FMC
	105.	NUT	NB40FMC
	106.	NUT	NK90FCU
	107.	SCREW	PMZ20P040FNI
	108.	SCREW	VMZ30P080FCU
	109.	WASHER (COPPER)	WB23FMC
	110.	WASHER (COPPER)	WS40FMC
	111.	CAPACITOR (C1 0.047/AC250V)	ACE1004
	112.	CAPACITOR (C2 0.047/AC250V)	ACE1004
	113.	• • • • •	
	114.	MICA CAPACITOR (C3, C4, C5,C6)	CMA221J500
	115.	• • • • •	
	116.	• • • • •	
	117.	SOCKET(3P)	
⚠	118.	FUSE (FU1 T1A)	AEK-402
	119.	EQUALIZER AMP MODULE (IC1, IC2)	AXX1018
	120.	FLAT AMP MODULE (IC3,IC4)	AXX1019
	121.	FERITE CORE (L1)	ATX1015
	122.	FERITE CORE (L2)	ATX1015
	123.	LAMP (PL1 8V/100MA)	AEL-176
	124.	LAMP (PL2 8V/100MA)	AEL-176
	125.	PUSH SWITCH (S1 POWER)	ASG-545
	126.	LINE TRANSFORMER (T1)	ATV1007
	127.	LINE TRANSFORMER (T2)	ATV1007
	128.	LINE TRANSFORMER (T3)	ATV1007
	129.	LINE TRANSFORMER (T4)	ATV1007
⚠	130.	POWER TRANSFORMER (T5)	ATT1141
⚠	131.	POWER TRANSFORMER (T6)	ATT1141
⚠	132.	POWER TRANSFORMER (T7)	ATT1142
	133.	VARIABLE RESISTOR (VR1)	ACW1011
	134.	VARIABLE RESISTOR (VR2)	ACW1011
	135.	VARIABLE RESISTOR (VR3)	ACW1012
◉	136.	PIN JACK -L ASS'Y	AWZ3247
◉	137.	PIN JACK -R ASS'Y	AWZ3248
◉	138.	BALANCE -L ASS'Y	AWZ3249
◉	139.	BALANCE -R ASS'Y	AWZ3250
◉	140.	CR -L ASS'Y	AWZ3251
◉	141.	CR -R ASS'Y	AWZ3252
◉	142.	POWER SUPPLY -L ASS'Y	AWZ3253
◉	143.	POWER SUPPLY -R ASS'Y	AWZ3254
◉	144.	DIODE -L ASS'Y	AWZ3255
◉	145.	DIODE -R ASS'Y	AWZ3256
◉	146.	MAIN CONTROL ASS'Y	AWZ3257
	147.	FUNCTION SW ASS'Y	
	148.	FRONT SW-A ASS'Y	
	149.	FRONT SW-B ASS'Y	
◉	150.	REGULATOR ASS'Y	AWZ3261
	151.	SCREW	ABA1050
	152.	SCREW	ABA1027
	153.	SCREW	ABA1052
	154.	SCREW	PMZ30P050CAD
	155.	WASHER	ABF1022
	156.	WASHER	WA25F065M050
	157.	WASHER	WA32C070S050
	158.	SPACER	ABF1002
	159.	POLISING CLOTH	E33-009
	160.	FRONT SW-D ASS'Y	
	161.	FRONT SW-C ASS'Y	
	162.	CONTROL SHIELD PLATE	
	163.	POWER SW SPACER	
	164.	BONNET CUSHION	
	165.	FUNCTION SPACER	
	166.	SHEET A	
	167.	SHEET B	

1.2 PACKING





The screw which is shown in the figure above is PMZ30P050CAD, the washer is ABF1022.

1.3 EXTERIOR


See pages 7 to 10
66
69
164
103
166
68
67
103
165
147
45
95
13
16
20
44
3
10
9
23
24
7
82
13
107
4
97
5
107
83
97
13
8
165
55
12
56
12
6
135
108
1
153
99
60
21
106
1
153
70
16
20
46
57
71
57
46
14
20
18

1.4 INTERIOR(1)



1.5 INTERIOR(2)



2. SCHEMATIC AND P.C.BOARDS CONNECTION DIAGRAM



* 1. This switch is turned off by inserting the plug to the RCA pin jack.



1. RESISTORS:
Indicated in Ω , 1/4W, 1/6W and 1/8W, ± 5% tolerance unless otherwise noted k; k Ω , M; M Ω , (F); ± 1%, (G); ± 2%, (K); ± 10%, (M); ± 20% tolerance.

2. CAPACITORS:
Indicated in capacity (μ F)/voltage (V) unless otherwise noted p; pF. Indication without voltage is 50V except electrolytic capacitor.

3. VOLTAGE, CURRENT:
▭ ; Signal voltage in rated output.
▱ ; DC voltage (V) at not input signal.
Value in ( ) is DC voltage at rated power.
⇦mA ; DC current at no input signal.

4. OTHERS:
➡ ; Signal route.
⊘ ; Adjusting point
The ⚠ mark found on some component parts indicates the importance of the safety factor of the part. Therefore, when replacing, be sure to use parts of identical designation.
※ marked capacitors and resistors have parts numbers.

This is the basic schematic diagram, but the actual circuit may vary due to improvements in design.

5.SWITCHES (The underline indicates the switch position.)
PIN JACK-L assembly, PIN JACK-R assembly
S101, S102: FUNCTION
BALANCE-TAPE2-TAPE1/DAT-TUNER-PHONO
-CD-LINE1-LINE2-LINE3-LINE4-LINE5
FUNCTION SW assembly
S601: FUNCTION

FRONT SW-A assembly
S611: ABSOLUTE 0 ° – 180 °
S612: OUT PUT OFF-1-2-1+2
FRONT SW-B assembly
S621: REC OUT ON-OFF
S622: BALANCE INPUT 1 – 2

Outside of P. C. BOARD Assembly
S1: POWER ON-OFF

PIN JACK-L ASS'Y(AWZ3247)



CR-L ASS'Y(AWZ3251)







PIN JACK-R ASS'Y(AWZ3248)



CR-R ASS'Y(AWZ3252)



POWER SUPPLY-L ASS'Y (AWZ3253)





TO MAIN CONTROL ASS'Y CN405,410

STEPPING MOTOR AXM1010

ASS'Y (ACW1011)



DIODE-L ASS'Y (AWZ3255)



T5
POWER TRANS.
ATT1141



TO T7 TRANS. DIODE-R ASS'Y (AWZ3256)



T6
POWER TRANS.
ATT1141



TO T7 TRANS.

POWER SUPPLY-R ASS'Y (AWZ3254)





TO MAIN CONTROL ASS'Y CN414

TO MAIN CONTROL ASS'Y CN415



BALANCE-L ASS'Y (AWZ3249)



TO MAIN CONTROL ASS'Y CN411











BALANCE-R ASS'Y (AWZ3250)



TO MAIN CONTROL ASS'Y CN412





This P.C.B. connection diagram is viewed from the foil side.



EXCLUSIVE


PIN JACK-R ASS'Y(AWZ3548)
TO MAIN CONTROL ASS'Y CN404
TO MAIN CONTROL ASS'Y CN405
PHONO
CD
TUNER
LINE1
LINE2
LINE3
LINE4
LINE5
TAPE1
TAPE2
REC SELECT
REC
R-CH


CR-R ASS'Y(AWZ3525)
TO MAIN CONTROL ASS'Y CN404
R CH
IC3
FLAT AMP MODULE
(RIO1XXA)
VOLUME ASS'Y(ACW1011)
STEPPING MOTOR
RIO1MXA
RED
BLUE
WHITE
YELLOW
TO MAIN CONTROL ASS'Y CN404,CN405
CR-L ASS'Y(AWZ3521)
TO MAIN CONTROL ASS'Y CN403
L CH


PIN JACK-L ASS'Y(AWZ3547)
TO MAIN CONTROL ASS'Y CN403
TO MAIN CONTROL ASS'Y CN402
PHONO
CD
TUNER
LINE1
LINE2
LINE3
LINE4
LINE5
TAPE1
TAPE2
REC SELECT
REC
L-CH



FUNCTION SW ASS'Y



REGULATOR ASS'Y(SW2250)







This P.C.B. connection diagram is viewed from the foil side.

NOTE

1. This P.C.B connection diagram is viewed from the parts mounted side.
2. The parts which have been mounted on the board can be replaced with those shown with the corresponding wiring symbols listed in the following Table.

P.C.B. pattern diagram indication	Corresponding part symbol	Part Name
Q504 (E)	or	Transistor
Q215	or	Radiator type transistor
D203	D203	Diode
R237	R237	Resistor
C513	+	Capacitor (Polarity)
C518		Capacitor (Non-polarity)

Others

P.C.B. pattern diagram indication	Part Name
IC	IC
S	Switch
RY	Relay
L	Coil
F	Filter
VR	Variable resistor or Semi-fixed resistor

3. The capactor terminal marked with ◎ (double circles) shows negatine termianl.
4. The diode terminal marked with ◎ (double circles) shows cathode side.
5. The transistor terminal to which E is affixed shows the emitter.




TO POWER SUPPLY-L ASS'Y CN301
TO POWER SUPPLY-R
Q443 Q447
Q441, Q445
IC431
IC433
IC435
IC422
IC421
Q448
Q501
Q417
IC402
IC409
IC403
Q408
Q402
Q404
Q406
Q414
Q410
Q416
Q412
IC408
IC406
IC401
IC404
Q401
Q407, Q403
Q405
Q413
Q409
Q411
Q415
IC405
IC407
TO PINJACK-L ASS'Y CN103
TO PINJACK-L ASS'Y CN101
TO PINJACK-L ASS'Y S101 MOTOR
TO PINJACK-R ASS'Y CN102
TO PINJACK-R ASS'Y S102 MOTOR
TO PINJACK-R ASS'Y CN104
AWZ3257
AP1470-B
FRONT SW-A ASS'Y
FRONT SW-C ASS'Y
FRONT SW-B ASS'Y
FRONT SW-D ASS'Y
OUTPUT
S612
ABS. PHASE
S611
BAL 1/2
S622
REC ON/OFF
S621
FUNCTION SW ASS'Y
S601
REGULATOR ASS'Y(AWZ3261)
AWZ326
T7
ATT1142
+ 12V (BLACK)
+ 12V (RED)
+ 5V (WHITE)
+ 5V (BROWN)
LAMP (GREEN)
LAMP (BLUE)
-24V (GRAY)
-24V (ORANGE)
GRAY
WHITE
FU1
1A
AEK-402
C1
0.047
ACE1004
L1
ATX1015
S1
POWER
ASG-545
C2
0.047
ACE1004
L2
ATX1015
AC220~230V
50/60Hz
BROWN
BLUE
ADG1093
TO T5, T6 POWER TRANS
TO T5, T6 POWER TRANS


MAIN CONTROL ASS'Y (AWZ3257)
POTENTIAL DIFFERENCE DETECTOR
Q401 RN2201
Q403,405 2SC2878
Q409,411 2SC2878
Q407,413,415 RN1201
Q402 RN2201
Q404,406 2SC287
Q410,412 2SC2878
Q408 RN1201
Q414,416 RN1201
IC401,402 UPD4030BC CODE CONVERTER
IC403 TC4001BP CODE CONVERTER
IC404 RC4558DXP D/A CONVERTER
IC405 IC407 TC4023BP TA7291S MOTOR DRIVER FOR FUNCTION SW
IC406 IC408 TC4023BP TA7291S MOTOR DRIVER FOR FUNCTION SW
IC431 ~ IC435 TC4001BP REC SELECTOR
Q441 ~ Q448 RN1201 REC SELECTOR
IC436 TC4011BP REC SELECTOR
IC422 TC4025BP PHONO FUNCTION DETECTOR
IC421 TC4078BP MUTING
FUNCTION SW ASS'Y
Q601,602 2SC1845 CONSTANT CURRENT
S601 FRONT FUNCTION SENSOR
Q501 2SC3923 RELAY SW
Q417 RN1203 SQUARE WAVE GENERATOR
IC409 RC4558DXP SQUARE WAVE GENERATOR
IC441 RC4558DXP BUFFER
Q431 RN1203 MOTOR STOP SW
SQUARE WAVE GENERATOR
Q481 RN1203
Q483 RN1203
Q482 RN1203
Q484 RN1201
Q485 RN1201
IC451 RC4558DXP
Q451 RN2201
Q453,455,457,459,461 2SC2878
Q463,465 RN1201
Q467,469 2SA992
Q452 RN2201
Q454,456 2SC2878
Q460,462 2SC2878
Q458,464,466 RN1201
Q468,470 2SA992
Q407,413,415 RN1201
Q408 RN1201
Q414,416 RN1201
CN401
CN402
CN403
CN404
CN405
CN406
CN415
CN416
CN601
L ch
R ch
MOTOR
+5V
+12V
2 LINE 4
1 LINE 5
9 TAPE 1
10 TAPE 2
EQ POWER
EQ ON : 4.4
EQ OFF : 0


DIFFERENCE DETECTOR
MOTOR DRIVER FOR VOLUME VR
IC442 TC4066BP
IC445 TA7291S
IC447 TA7291S
Q467,469 2SA992
Q449,451 1SS252
Q485 RN1201
IC443 TC4011BP
Q484 RN1201
POTENTIAL DIFFERENCE DETECTOR
Q460,462 2SC2878
IC444 TC4066BP
IC446 TA7291S
IC448 TA7291S
Q458,464,466 RN1201
Q468,470 2SA992
Q471 RN1203 MOTOR STOP SW
Q491 2SC1845 VOLTAGE ADJUSTER
Q495 2SC1845 VOLTAGE REFERENCE
Q493 2SC1845 CURRENT REGULATOR
Q494 2SC1845 CURRENT REGULATOR
Q492 2SC1845 VOLTAGE ADJUSTER
Q504 2SA1529 OUTPUT RELAY DRIVE
Q505 RN2203 DRIVE
Q506 2SA1529 OUTPUT RELAY DRIVE
Q507 RN2203 DRIVE
Q503 2SC1845 FUNCTION MUTE SW
Q502 RN1203 FUNCTION MUTE SW
Q508 RN1203 OUTPUT RELAY DRIVE
Q509 2SC1845 POWER MUTE ON/OFF
Q510 RN1201 POWER MUTE ON/OFF
Q511 RN1201 POWER MUTE ON/OFF
REGULATOR ASS'Y(1/2) (AWZ3261)
Q631 2SD1275 REGULATOR
REGULATOR ASS'Y(2/2) (AWZ3261)
IC632 M5F7812L REGULATOR
IC631 M5F7812L REGULATOR
IC464 M5F78M05L 5V REG
IC463 M5F79M24L -24V REG
Q521 2SA1306 REGULATOR
Q522 2SK246 REGULATOR
VOLUME ASS'Y(ACW1012)
FRONT VOLUME
VR3
FRONT SW-A ASS'Y
S612 : ASD1009
FRONT SW-B ASS'Y
S622 BALANCE INPUT
FRONT SW-C ASS'Y
S611 ABSOLUTE PHASE
S611 : ASD1008
FRONT SW-D ASS'Y
S621 REC OUT
S621 : ASD1008
T7 ATT1142
POWER S30-345
AC220~230V 50/60Hz
AC01093
MOTOR STOP: 6
NORMAL : 0
FUNC. NORMAL : 5
FUNC. MUTE : 0
REC ON : 4.9
REC OFF : 0
+12V (MOTOR)
VR401 — VR404 VR POSITION DETECTION CENTER CONTROL
R559, 556, 566 : ACN1079
R557, 558, 564, 568 : ACN1080
R567 : ACN1081
R591, 592, 594, 595, 596 : ACN-157
VR401, 402, 404 : VRTS6VS103
VR403 : VRTS6V221

3. ELECTRICAL PARTS LIST

NOTES:

- *Parts without part number cannot be supplied.*
- *Parts marked by "◉" are not always kept in stock. Their delivery time may be longer than usual or they may be unavailable.*
- *The ⚠ mark found on some component parts indicates the importance of the safety factor of the part. Therefore, when replacing, be sure to use parts of indetical designation.*
- *When ordering resistors, first convert resistance values into code form as shown in the following examples.*

Ex.1 When there are 2 effective digits (any digit apart from 0), such as 560 ohm and 47k ohm (tolerance is shown by J = 5%, and K = 10%)

560Ω	*56 × 10¹*	*561*	*RD1/4PS [5][6][1] J*
47kΩ	*47 × 10³*	*473*	*RD1/4PS [4][7][3] J*
0.5Ω	*0R5*		*RN2H [0][R][5] K*
1Ω	*010*		*RS1P [0][1][0] K*

Ex.2 When there are 3 effective digits (such as in high precision metal film resistors).

5.62kΩ	*562 × 10¹*	*5621*	*RN1/4SR [5][6][2][1] F*

Mark	No.	Description	Part No.
PIN JACK -L ASS'Y (AWZ3247)			
SWITCH			
	S101	SWITCH (FUNCTION)	ASD1011
RELAIES			
	RY101	RELAY (LINE 4 OUT)	ASR1018
	RY103	RELAY (LINE 5 OUT)	ASR1018
	RY105	RELAY (TAPE 1 REC)	ASR1018
	RY107	RELAY (TAPE 2 REC)	ASR1018
COILS			
	L101	INDUCTOR (270μH)	ATH1010
	L103	COIL (0.47μH)	ATH1052
CAPACITORS			
	C101	MICA CAPACITOR	CMA220J500
	C103	MICA CAPACITOR	CMA271J500
	C105	CERAMIC CAPACITOR	CCDSL271K500
	C107	CERAMIC CAPACITOR	CCDSL271K500
	C109	CERAMIC CAPACITOR	CCDSL271K500
	C111	CERAMIC CAPACITOR	CCDSL271K500
	C113	CERAMIC CAPACITOR	CCDSL271K500
	C115	CERAMIC CAPACITOR	CCDSL271K500
	C117	CERAMIC CAPACITOR	CCDSL271K500
	C119	CERAMIC CAPACITOR	CCDSL271K500
	C121	MICA CAPACITOR	CMA221J500
	C123	MICA CAPACITOR	CMA301J500
	C125	CERAMIC CAPACITOR	CKDYB391K500
	C127	CERAMIC CAPACITOR	CKDYB391K500
	C129	CERAMIC CAPACITOR	CKDYB391K500
	C131	CERAMIC CAPACITOR	CKDYB391K500
	C133	ELECTR.CAPACITOR	CEAS100M50
	C135	ELECTR.CAPACITOR	CEAS100M50
	C137	ELECTR.CAPACITOR	CEAS100M50
	C139	ELECTR.CAPACITOR	CEAS100M50
	C141	CERAMIC CAPACITOR	CKDYB103K50
	C143	AUDIO FILM CAPACITOR	CFTXA103J50
	C171	CERAMIC CAPACITOR	CKDYB103K50
	C173	CERAMIC CAPACITOR	CCDSL560J50
	C175	CERAMIC CAPACITOR	CKDYB682K50
	C177	CERAMIC CAPACITOR	CKDYB682K50
	C179	CERAMIC CAPACITOR	CKDYB682K50
	C181	CERAMIC CAPACITOR	CKDYB682K50
RESISTORS			
	R131	CARBON FILM RESISTOR	RDR1/6PU103J
	R133	CARBON FILM RESISTOR	RDR1/6PU103J
	R135	CARBON FILM RESISTOR	RDR1/6PU103J
	R137	CARBON FILM RESISTOR	RDR1/6PU103J
	R141	CARBON FILM RESISTOR	RDR1/6PU102J
		OTHER RESISTORS	RDR1/4PM□□□J
OTHER			
	CN	PIN JACK 1-P (OUTPUT 1)	AKB1162
PIN JACK -R ASS'Y (AWZ3248)			
SWITCH			
	S102	SWITCH (FUNCTION)	ASD1011
RELAIES			
	RY102	RELAY (LINE 4 OUT)	ASR1018
	RY104	RELAY (LINE 5 OUT)	ASR1018
	RY106	RELAY (TAPE 1 REC)	ASR1018
	RY108	RELAY (TAPE 2 REC)	ASR1018
COILS			
	L102	INDUCTOR (270μH)	ATH1010
	L104	COIL (0.47μH)	ATH1052
CAPACITORS			
	C102	MICA CAPACITOR	CMA220J500
	C104	MICA CAPACITOR	CMA271J500
	C106	CERAMIC CAPACITOR	CCDSL271K500
	C108	CERAMIC CAPACITOR	CCDSL271K500
	C110	CERAMIC CAPACITOR	CCDSL271K500
	C112	CERAMIC CAPACITOR	CCDSL271K500

Mark	No.	Description	Part No.
	C114	CERAMIC CAPACITOR	CCDSL271K500
	C116	CERAMIC CAPACITOR	CCDSL271K500
	C118	CERAMIC CAPACITOR	CCDSL271K500
	C120	CERAMIC CAPACITOR	CCDSL271K500
	C122	MICA CAPACITOR	CMA221J500
	C124	MICA CAPACITOR	CMA301J500
	C126	CERAMIC CAPACITOR	CKDYB391K500
	C128	CERAMIC CAPACITOR	CKDYB391K500
	C130	CERAMIC CAPACITOR	CKDYB391K500
	C132	CERAMIC CAPACITOR	CKDYB391K500
	C134	ELECTR.CAPACITOR	CEAS100M50
	C136	ELECTR.CAPACITOR	CEAS100M50
	C138	ELECTR.CAPACITOR	CEAS100M50
	C140	ELECTR.CAPACITOR	CEAS100M50
	C142	CERAMIC CAPACITOR	CKDYB103K50
	C144	AUDIO FILM CAPACITOR	CFTXA103J50
	C172	CERAMIC CAPACITOR	CKDYB103K50
	C174	CERAMIC CAPACITOR	CCDSL560J50
	C176	CERAMIC CAPACITOR	CKDYB682K50
	C178	CERAMIC CAPACITOR	CKDYB682K50
	C180	CERAMIC CAPACITOR	CKDYB682K50
	C182	CERAMIC CAPACITOR	CKDYB682K50
RESISTORS			
	R132	CARBON FILM RESISTOR	RDR1/6PU103J
	R134	CARBON FILM RESISTOR	RDR1/6PU103J
	R136	CARBON FILM RESISTOR	RDR1/6PU103J
	R138	CARBON FILM RESISTOR	RDR1/6PU103J
	R142	CARBON FILM RESISTOR	RDR1/6PU102J
		OTHER RESISTORS	RDR1/4PM□□□J
OTHER			
	CN	PIN JACK 1-P (OUTPUT 1)	AKB1162

BALANCE -L ASS'Y (AWZ3249)

RELAY			
	RY151	RELAY (BALANCE IN 1/2)	ASR1018
CAPACITOR			
	C151	ELECTR.CAPACITOR	CEAS100M50
RESISTORS			
		ALL RESISTORS	RDR1/4PM□□□J

BALANCE -R ASS'Y (AWZ3250)

RELAY			
	RY152	RELAY (BALANCE IN 1/2)	ASR1018
CAPACITOR			
	C152	ELECTR.CAPACITOR	CEAS100M50
RESISTORS			
		ALL RESISTORS	RDR1/4PM□□□J

Mark	No.	Description	Part No.

CR -L ASS'Y (AWZ3251)

RELAIES			
	RY201	RELAY (REC ON/OFF)	ASR1018
	RY203	RELAY (ABSOLUTE PHASE 0°/180°)	ASR1018
	RY205	RELAY (OUTPUT ON/OFF)	ASR1018
	RY207	RELAY (OUTPUT 2)	ASR1018
CAPACITORS			
	C201	ELECTR.CAPACITOR (1000μF/25V)	ACH1183
	C203	CAPACITOR (0.12μF)	ACE-095
	C205	CAPACITOR	CQSXA122J160
	C207	CAPACITOR (0.033μF)	ACE-094
	C209	ELECTR.CAPACITOR (22μF/50V NP)	ACH1182
	C211	CAPACITOR	CQMXA123J100
	C213	ELECTR.CAPACITOR (22μF/50V NP)	ACH1182
	C215	ELECTR.CAPACITOR (220μF/25V NP)	ACH1184
	C217	ELECTR.CAPACITOR (220μF/25V NP)	ACH1184
	C219	ELECTR.CAPACITOR (330μF/50V)	ACH1178
	C221	ELECTR.CAPACITOR	CEAS100M50
	C223	ELECTR.CAPACITOR	CEAS100M50
	C225	ELECTR.CAPACITOR	CEAS100M50
	C227	ELECTR.CAPACITOR	CEAS100M50
	C229	MICA CAPACITOR	CMA101J500
	C231	MICA CAPACITOR	CMA820J500
	C233	CERAMIC CAPACITOR	CCDSL101J50
	C235	CERAMIC CAPACITOR	CKDYB102K50
	C237	CERAMIC CAPACITOR	CCDSL101J50
	C239	CERAMIC CAPACITOR	CCDSL101J50
	C251	MICA CAPACITOR	CMA820J500
	C253	CERAMIC CAPACITOR	CKDYB681K50
RESISTORS			
		ALL RESISTORS	RDR1/4PM□□□J
OTHER			
		STAR TERMINAL B	AKE1028

CR -R ASS'Y (AWZ3252)

RELAIES			
	RY202	RELAY (REC ON/OFF)	ASR1018
	RY204	RELAY (ABSOLUTE PHASE 0°/180°)	ASR1018
	RY206	RELAY (OUTPUT ON/OFF)	ASR1018
	RY208	RELAY (OUTPUT 2)	ASR1018

Mark	No.	Description	Part No.
CAPACITORS			
	C202	ELECTR.CAPACITOR (100μF/25V)	ACH1183
	C204	CAPACITOR (0.12μF)	ACE-095
	C206	CAPACITOR	CQSXA122J160
	C208	CAPACITOR (0.033μF)	ACE-094
	C210	ELECTR.CAPACITOR (22μF/50V NP)	ACH1182
	C212	CAPACITOR	CQMXA123J100
	C214	ELECTR.CAPACITOR (22μF/50V NP)	ACH1182
	C216	ELECTR.CAPACITOR (220μF/25V NP)	ACH1184
	C218	ELECTR.CAPACITOR (220μF/25V NP)	ACH1184
	C220	ELECTR.CAPACITOR (330μF/50V)	ACH1178
	C222	ELECTR.CAPACITOR	CEAS100M50
	C224	ELECTR.CAPACITOR	CEAS100M50
	C226	ELECTR.CAPACITOR	CEAS100M50
	C228	ELECTR.CAPACITOR	CEAS100M50
	C230	MICA CAPACITOR	CMA101J500
	C232	MICA CAPACITOR	CMA820J500
	C234	CERAMIC CAPACITOR	CKDYB102K50
	C236	CERAMIC CAPACITOR	CCDSL101J50
	C238	CERAMIC CAPACITOR	CKDYB102K50
	C240	CERAMIC CAPACITOR	CKDYB102K50
	C252	MICA CAPACITOR	CMA820J500
	C254	CERAMIC CAPACITOR	CKDYB681K50
RESISTORS			
	ALL RESISTORS		RDR1/4PM□□□J
OTHER			
	STAR TERMINAL B		AKE1028

POWER SUPPLY -L ASS'Y (AWZ3253)

Mark	No.	Description	Part No.
SEMICONDUCTORS			
	Q301	TRANSISTOR	2SA970
	Q303	TRANSISTOR	2SC2240
	Q305	TRANSISTOR	2SA1263N
	Q307	TRANSISTOR	2SC3180N
	Q309	TRANSISTOR	2SC2240
	Q311	TRANSISTOR	2SA970
	Q313	TRANSISTOR	2SC2240
	Q315	TRANSISTOR	2SA970
	Q351	TRANSISTOR	2SA970
	Q353	TRANSISTOR	2SC2240
	Q355	TRANSISTOR	2SA1263N
	Q357	TRANSISTOR	2SC3180N
	Q359	TRANSISTOR	2SC2240
	Q361	TRANSISTOR	2SA970
	Q363	TRANSISTOR	2SC2240
	Q365	TRANSISTOR	2SA970
	D301	LED	AEL1096
	D303	LED	AEL1096
	D305	ZENER DIODE	RD11ESB
	D307	ZENER DIODE	RD11ESB
	D309	DIODE	11E2
	D311	DIODE	11E2
	D351	LED	AEL1096
	D353	LED	AEL1096
	D355	ZENER DIODE	RD5.6ESB
	D357	ZENER DIODE	RD5.6ESB
	D359	DIODE	11E2
	D361	DIODE	11E2
RELAIES			
	RY301	RELAY	ASR1018
	RY303	RELAY	ASR1018
CAPACITORS			
	C301	ELECTR.CAPACITOR (2200μF/42V)	ACH1174
	C303	ELECTR.CAPACITOR (2200μF/42V)	ACH1175
	C305	MICA CAPACITOR	CMA151J500
	C307	MICA CAPACITOR	CMA151J500
	C309	ELECTR.CAPACITOR (330μF/50V)	ACH1178
	C311	ELECTR.CAPACITOR (330μF/50V)	ACH1179
	C313	ELECTR.CAPACITOR	CEEA100M25
	C315	ELECTR.CAPACITOR	CEEA100M25
	C317	ELECTR.CAPACITOR (330μF/50V)	ACH1178
	C319	ELECTR.CAPACITOR (330μF/50V)	ACH1179
	C321	ELECTR.CAPACITOR	CEAS100M50
	C351	ELECTR.CAPACITOR (6800μF/50V)	ACH1172
	C353	ELECTR.CAPACITOR (6800μF/50V)	ACH1173
	C355	MICA CAPACITOR	CMA151J500
	C357	MICA CAPACITOR	CMA151J500
	C359	ELECTR.CAPACITOR (330μF/50V)	ACH1178
	C361	ELECTR.CAPACITOR (330μF/50V)	ACH1179
	C363	ELECTR.CAPACITOR	CEEA100M25
	C365	ELECTR.CAPACITOR	CEEA100M25
	C367	ELECTR.CAPACITOR (470μF/50V)	ACH1176
	C369	ELECTR.CAPACITOR (470μF/50V)	ACH1177
RESISTORS			
	R317	CARBON FILM RESISTOR	RDR1/2PM153J
	OTHER RESISTORS		RDR1/4PM□□□J
OTHERS			
	MICA SHEET		AEC1163
	STAR TERMINAL A		AKE1027
	STAR TERMINAL B		AKE1028

Mark	No.	Description	Part No.
		SCREW	PMB30P100FCU

POWER SUPPLY -R ASS'Y (AWZ3254)

Mark	No.	Description	Part No.
SEMICONDUCTORS			
	Q302	TRANSISTOR	2SA970
	Q304	TRANSISTOR	2SC2240
	Q306	TRANSISTOR	2SA1263N
	Q308	TRANSISTOR	2SC3180N
	Q310	TRANSISTOR	2SC2240
	Q312	TRANSISTOR	2SA970
	Q314	TRANSISTOR	2SC2240
	Q316	TRANSISTOR	2SA970
	Q352	TRANSISTOR	2SA970
	Q354	TRANSISTOR	2SC2240
	Q356	TRANSISTOR	2SA1263N
	Q358	TRANSISTOR	2SC3180N
	Q360	TRANSISTOR	2SC2240
	Q362	TRANSISTOR	2SA970
	Q364	TRANSISTOR	2SC2240
	Q366	TRANSISTOR	2SA970
	D302	LED	AEL1096
	D304	LED	AEL1096
	D306	ZENER DIODE	RD11ESB
	D308	ZENER DIODE	RD11ESB
	D310	DIODE	11E2
	D312	DIODE	11E2
	D352	LED	AEL1096
	D354	LED	AEL1096
	D356	ZENER DIODE	RD5.6ESB
	D358	ZENER DIODE	RD5.6ESB
	D360	DIODE	11E2
	D362	DIODE	11E2
RELAIES			
	RY302	RELAY	ASR1018
	RY304	RELAY	ASR1018
CAPACITORS			
	C302	ELECTR.CAPACITOR (2200μF/42V)	ACH1174
	C304	ELECTR.CAPACITOR (2200μF/42V)	ACH1175
	C306	MICA CAPACITOR	CMA151J500
	C308	MICA CAPACITOR	CMA151J500
	C310	ELECTR.CAPACITOR (330μF/50V)	ACH1178
	C312	ELECTR.CAPACITOR (330μF/50V)	ACH1179
	C314	ELECTR.CAPACITOR	CEEA100M25
	C316	ELECTR.CAPACITOR	CEEA100M25
	C318	ELECTR.CAPACITOR (330μF/50V)	ACH1178
	C320	ELECTR.CAPACITOR (330μF/50V)	ACH1179
	C322	ELECTR.CAPACITOR	CEAS100M50
	C352	ELECTR.CAPACITOR (6800μF/50V)	ACH1172
	C354	ELECTR.CAPACITOR (6800μF/50V)	ACH1173
	C356	MICA CAPACITOR	CMA151J500
	C358	MICA CAPACITOR	CMA151J500
	C360	ELECTR.CAPACITOR (330μF/50V)	ACH1178
	C362	ELECTR.CAPACITOR (330μF/50V)	ACH1179
	C364	ELECTR.CAPACITOR	CEEA100M25
	C366	ELECTR.CAPACITOR	CEEA100M25
	C368	ELECTR.CAPACITOR (470μF/50V)	ACH1176
	C370	ELECTR.CAPACITOR (470μF/50V)	ACH1177
RESISTORS			
	R318	CARBON FILM RESISTOR	RDR1/2PM153J
		OTHER RESISTORS	RDR1/4PM□□□J
OTHERS			
		MICA SHEET	AEC1143
		STAR TERMINAL A	AKE1027
		STAR TERMINAL B	AKE1028
		SCREW	PMB30P100FCU

DIODE -L ASS'Y (AWZ3255)

Mark	No.	Description	Part No.
SEMICONDUCTORS			
	D313	DIODE	11DF2FD
	D315	DIODE	11DF2FD
	D317	DIODE	11DF2FD
	D319	DIODE	11DF2FD
	D363	DIODE	31DF2FC
	D365	DIODE	31DF2FC
	D367	DIODE	31DF2FC
	D369	DIODE	31DF2FC
OTHER			
		STAR TERMINAL B	AKE1028

DIODE -R ASS'Y (AWZ3256)

Mark	No.	Description	Part No.
SEMICONDUCTORS			
	D314	DIODE	11DF2FD
	D316	DIODE	11DF2FD
	D318	DIODE	11DF2FD
	D320	DIODE	11DF2FD
	D364	DIODE	31DF2FC
	D366	DIODE	31DF2FC
	D368	DIODE	31DF2FC
	D370	DIODE	31DF2FC
OTHER			
		STAR TERMINAL B	AKE1028

Mark	No.	Description	Part No.

MAIN CONTROL ASS'Y (AWZ3257)

SEMICONDUCTORS

	IC401, 402	LOGIC IC	UPD4030BC
	IC403	LOGIC IC	TC4001BP
	IC404	OP-AMP IC	RC4558DXP
	IC405, 406	LOGIC IC	TC4023BP
	IC407, 408	DRIVER IC	TA7291S
	IC409	OP-AMP IC	RC4558DXP
	IC421	LOGIC IC	TC4078BP
	IC422	LOGIC IC	TC4025BP
	IC431–435	LOGIC IC	TC4001BP
	IC436	LOGIC IC	TC4011BP
	IC441	OP-AMP IC	RC4558DXP
	IC442	LOGIC IC	TC4066BP
	IC443	LOGIC IC	TC4011BP
	IC444	LOGIC IC	TC4066BP
	IC445–448	DRIVER IC	TA7291S
	IC451	OP-AMP IC	RC4558DXP
	IC463	REGURATOR IC	M5F79M24L
	IC464	REGURATOR IC	M5F78M05L
	Q401, 402	TRANSISTOR	RN2201
	Q403–406	TRANSISTOR	2SC2878
	Q407, 408	TRANSISTOR	RN1201
	Q409–412	TRANSISTOR	2SC2878
	Q413–416	TRANSISTOR	RN1201
	Q417	TRANSISTOR	RN1203
	Q431	TRANSISTOR	RN1203
	Q441–448	TRANSISTOR	RN1201
	Q451, 452	TRANSISTOR	RN2201
	Q453–456	TRANSISTOR	2SC2878
	Q457, 458	TRANSISTOR	RN1201
	Q459–462	TRANSISTOR	2SC2878
	Q463–466	TRANSISTOR	RN1201
	Q467–470	TRANSISTOR	2SA992
	Q471	TRANSISTOR	RN1203
	Q481–483	TRANSISTOR	RN1203
	Q484, 485	TRANSISTOR	RN1201
	Q491–495	TRANSISTOR	2SC1845
	Q501	TRANSISTOR	2SC3923
	Q502	TRANSISTOR	RN1203
	Q503	TRANSISTOR	2SC1845
	Q504	TRANSISTOR	2SA1529
	Q505	TRANSISTOR	RN2203
	Q506	TRANSISTOR	2SA1529
	Q507	TRANSISTOR	RN2203
	Q508	TRANSISTOR	RN1203
	Q509	TRANSISTOR	2SC1845
	Q510, 511	TRANSISTOR	RN1201
	Q521	TRANSISTOR	2SA1306
	Q522	N-FET	2SK246
	D401–404	ZENER DIODE	RD3.0ESB2
	D405–408	DIODE	1SS252
	D409	ZENER DIODE	RD5.6ESB2
	D411	DIODE	1SS252
	D431–436	DIODE	1SS252
	D441–444	ZENER DIODE	RD3.0ESB2
	D445–452	DIODE	1SS252
	D453	ZENER DIODE	RD9.1ESB
	D454, 455	DIODE	1SS252
	D461, 462	DIODE	1SS252
	D463	ZENER DIODE	RD6.8ESB
	D464	DIODE	11E2
	D471	ZENER DIODE	RD13ESB
	D472	ZENER DIODE	RD33ESB2
	D473	DIODE	RB152
	D474, 475	DIODE	S1WB20
	D476, 477	DIODE	1SS252

CAPACITORS

C401, 402	MYLOR FILM CAPACITOR	CQMA473K50
C403–406	ELECTR.CAPACITOR	CEAS4R7M50
C407, 408	MYLOR FILM CAPACITOR	CQMA473K50
C409	AUDIO FILM CAPACITOR	CFTXA105J50
C414	MYLOR FILM CAPACITOR	CQMA473K50
C415	MYLOR FILM CAPACITOR	CQMA104K50
C421, 422	ELECTR.CAPACITOR	CEAS220M50
C431, 432	MYLOR FILM CAPACITOR	CQMA473K50
C433–436	MYLOR FILM CAPACITOR	CQMA683K50
C437, 438	MYLOR FILM CAPACITOR	CQMA473K50
C439	MYLOR FILM CAPACITOR	CQMA224K50
C440	ELECTR.CAPACITOR	CEAS331M16
C441	ELECTR.CAPACITOR	CEAS010M50
C442	ELECTR.CAPACITOR	CEAS331M16
C443	ELECTR.CAPACITOR	CEAS100M50
C444	ELECTR.CAPACITOR	CEAS102M16
C461	ELECTR.CAPACITOR	CEAS102M16
C462	ELECTR.CAPACITOR	CEAS470M16
C463	ELECTR.CAPACITOR	CEAS222M25
C464, 465	ELECTR.CAPACITOR	CEAS100M50
C466	ELECTR.CAPACITOR	CEAS471M25
C467	ELECTR.CAPACITOR	CEAS222M25
C468	ELECTR.CAPACITOR	CEAS220M50
C469	ELECTR.CAPACITOR	CEAS331M50
C470	ELECTR.CAPACITOR	CEAS102M50
C471	MYLOR FILM CAPACITOR	CQMA104K50
C472	ELECTR.CAPACITOR	CEAS222M16
C473	MYLOR FILM CAPACITOR	CQMA104K50
C474	ELECTR.CAPACITOR	CEAS220M50

RESISTORS

VR401, 402	VARIABLE RESISTOR (10k)	VRTS6VS103
VR403	VARIABLE RESISTOR (220)	VRTS6VS221
VR404	VARIABLE RESISTOR (10K)	VRTS6VS103

Mark	No.	Description	Part No.
	R401, 402	RESISTOR ARRAY (22k)	RA5S223J
	R403, 404	METALFILM RESISTER	RN1/4PC6042F
	R405, 406	METALFILM RESISTER	RN1/4PC3002F
	R407, 408	METALFILM RESISTER	RN1/4PC1502F
	R409, 410	METALFILM RESISTER	RN1/4PC7501F
	R411, 412	METALFILM RESISTER	RN1/4PC1242F
	R555, 556	METALFILM RESISTER (2.74K 1/4W)	ACN1079
	R557, 558	METALFILM RESISTER (3.01K 1/4W)	ACN1080
	R559, 560	METALFILM RESISTER	RN1/4PC4122F
	R561, 562	METALFILM RESISTER	RN1/4PC2401F
	R563	METALFILM RESISTER	RN1/2PC8201F
	R564	METALFILM RESISTER (3.01K 1/4W)	ACN1080
	R565	METALFILM RESISTER	RN1/4PC4122F
	R566	METALFILM RESISTER (2.74K 1/4W)	ACN1079
	R567	METALFILM RESISTER (4.99K 1/4W)	ACN1081
	R568	METALFILM RESISTER (3.01K 1/4W)	ACN1080
	R591, 592	FUSLIBLE RESISTOR (2.2 1/4W)	ACN-157
	R594–596	FUSLIBLE RESISTOR (2.2 1/4W)	ACN-157
	R597	FUSLIBLE RESISTOR	RFA1/4PL270J
	R598	METAL OXIDE RESISTOR	RS1LMF560J
	R599	CARBONFILM RESISTOR	RD1/4PM101J
		OTHER RESISTORS	RD1/8PM□□□J
OTHER			
	CN422	PLUG 8-P	AKM1071
		SCREW	PMB30P100FCU

FUNCTION SW ASS'Y

SEMICONDUCTORS			
	Q601, 602	TRANSISTOR	2SC1845
	D601	ZENER DIODE	RD5.1ESB2
SWITCH			
	S601	SWITCH (FUNCTION)	ASD1010
RESISTORS			
	R601–611	METALFILM RESISTER	RN1/4PC1200F
	R612	METALFILM RESISTER	RN1/4PC5900F
	R613	METALFILM RESISTER	RN1/4PC6201F

FRONT SW-A ASS'Y

SWITCHES			
	S612	SWITCH (OUTPUT)	ASD1009

Mark	No.	Description	Part No.

FRONT SW-B ASS'Y

SWITCHES			
	S622	SWITCH (BALANCE INPUT)	ASD1008

REGULATOR ASS'Y (AWZ3261)

SEMICONDUCTORS			
	IC631, 632	REGURATOR IC	M5F7812L
	Q631	TRANSISTOR	2SD1275
OTHER			
		SCREW	PMB30P100FCU

FRONT SW-C Ass'y

	S611	SWITCH	ASD1008

FRONT SW-D Ass'y

	S621	SWITCH (REC ON/OFF)	ASD1008

4. ADJUSTMENTS

VR POSITION DETECTION CENTER ADJUSTMENT

Step	*1 Measurement Location	Adjustment Location	Specifications
1	–	–	Set the main volume on the front panel to minimum, and turn on the power. Adjustment is possible with or without input.
2	Between TP6 and TP5	VR403	Adjust so that the measurement location value is 0V ± 2mV.
3	Between TP4 and TP3	VR404	
4	Between TP4 and TP1	VR401	
5	Between TP4 and TP2	VR402	
6	–	–	Repeat steps 2 and 3.

*1: Should be measured with digital voltmeter.

Note: After adjustment, turn up the front main volume gradually (slowly), and confirm so that the axles of VR1 and VR2 rotate little by little in response to the front main volume adjustment. (If one of the axle does not rotate and vibrates slightly, repeat the adjustment.)



Fig4-1 Top view



Fig4-2 Bottom view

4. RÈGLAGES

RÉGLAGE DU CANTRE DE DÉTECTION DE POSITION VR

Etape	*1 Point de mesure	Emplacement de l'ajustement	Spécifications
1	–	–	Régler de volume principal sur le panneau avant au minimum et mettre sous tension. L'ajustement est possible avec ou sans entrée.
2	Entre TP6 et TP5	VR403	Régler de façon à ce que la valeur du point de mesure soit de 0 ± 2mV.
3	Entre TP4 et TP3	VR404	
4	Entre TP4 et TP1	VR401	
5	Entre TP4 et TP2	VR402	
6	–	–	Répéter les étapes 2 et 3.

*1: Doit être mesurée avec un voltmètre numérique.

Remarque: Après l'ajustement, augmenter graduellement (lentement) le volume principal avant et confirmer que les axes de VR1 et VR2 tournent peu à peu en réponse au réglage du volume principal avant.
(Si l'un des axes ne tourne pas et vibre légèrement, répéter l'ajustement.)



Fig. 4-1 Vue inférieure



Fig. 4-2 Vue supérieure

4. AJUSTES

AJUSTE DEL CENTRO DE DETECCIÓN DE LA POSICIÓN DEL VR

Paso	*1 Lugar de medición	Lugar de ajuste	Especificaciones
1	–	–	Coloque el volumen principal del panel delantero al mínimo y conecte la alimentación. El ajuste es posible con o sin entrada.
2	Entre TP6 y TP5	VR403	Ajuste de forma que el valor en el lugar de ajuste sea 0V ± 2mV.
3	Entre TP4 y TP3	VR404	
4	Entre TP4 y TP1	VR401	
5	Entre TP4 y TP2	VR402	
6	–	–	Repita los pasos 2 y 3.

*1: Debe medirse con un voltímetro digital.

Nota: Después del ajuste, suba gradualmente (lentamente) el volumen principal delantero y confirme que los ejes de VR1 y VR2 giran poco a poco en respuesta al ajuste del volumen principal delantero.
(Si uno de los ejes no gira y vibra ligeramente, repita el ajuste.)



Fig. 4-1 Vista de abajo arriba



Fig. 4-2 Vista superior

5. FRONT PANEL FACILITIES



① Power switch(POWER)/indicator

Press to set the power ON/OFF.
When in the ON position,the indicator lights up.No sound will be heard from the speakers for about 6 seconds as a muting circuit is activated to prevent switching noise.

② Function selector switch(FUNCTION)

Use to select program source for playing.

[CD] ····· To play a compact disc player connected to CD terminal.
[PHONO] ····· To play a turntable connected to PHONO terminal.
[TUNER] ····· To play a stereo tuner connected to TUNER terminal.
[LINE1~LINE5] ····· To play AUDIO equipment connected to LINE terminals.
[TAPE1/DAT] ····· To play a cassette deck connected to TAPE1/DAT terminal.
[TAPE2] ····· To play a cassette deck connected to TAPE2 terminal.
[BALANCE] ····· To play AUDIO equipment connected to BALANCE terminal.

NOTE:
A motor is used to select the function.The function is activated 5 seconds (maximum) after it is selected (e.g. from LINE5 to BALANCE).

③ Volume control(VOLUME)

Use to adjust sound volume.Figures on the dial show the attenuation level when rated output level(1V) is considered to be 0dB.
At the [∞] position, sound will not be heard.

NOTE:
A motor is used to adjust the volume control.
The volume control is activated 2 seconds (maximum) after it is turned (e.g. from ∞ to 0 dB).

④ Balance input selector switch (BALANCE INPUT)

Select either of two balanced inputs.

1 ····· To play equipment connected to balance input 1.
2 ····· To play equipment connected to balance input 2.

⑤ Recording output on/off selector switch (REC ON/OFF)

[ON] ····· To output recording signal to terminals of TAPE1/DAT REC,TAPE2 REC and OUT terminals of LINE4 and LINE 5.
[OFF] ····· To stop output recording signal. When not recording,set the switch to OFF position in order to prevent a connected external terminal from interfering with this terminal, thus ensuring high quality sound.

6 Output selector switch (OUTPUT)

Use to select output terminal.

[OFF] ..... To stop signal output to both output terminals(OUTPUT1,and 2).

[1] ..... To output a signal to OUTPUT1 terminal(pin-plug) only.

[2] ..... To output a signal to OUTPUT2 terminal(cannon plug) only.

[1 + 2] ..... To output a signal to both output terminals(OUTPUT1 & 2).

7 Phase selector switch (ABSOLUTE PHASE)

Use to shift phase both output signals (L and R channels) 180 degrees. When this equipment is used as a component of a system,this feature is helpful to align the phases of appliances connected to this preamplifier.

0° ..... Set to this position normally.

180° ..... Use when the phases of equipment are not aligned.

CONNECTING BY CANNON PLUG

This appliance is equipped with cannon plugs for two input and one output terminals besides normal pin-jack plugs. When using cannon plugs,connect the balanced output terminal of this equipment to the balanced input terminal of an amplifier(such as an M6) using commercially available cannon plug connecting cords. Using balanced input prevents external noise interference thus enabling high quality sound.

Balance INPUT, OUTPUT



1 GND
2 COLD (−)
3 HOT (+)

NOTE:
When connecting the Cannon plug with the Pioneer EXCLUSIVE M6, adjust the ABSOLUTE PHASE switch to 180°.
(The M6 Balance INPUT is for 1 GND, 2 HOT (+), 3 COLD (−)).

6. SPECIFICATIONS

Amplifier section

Input terminals (sensitivity/impedance)
- PHONO MM ..... 2.5 mV/50 kΩ
- CD ..... 150 mV/50 kΩ
- TUNER ..... 150 mV/50 kΩ
- LINE1, 2, 3, 4, 5 ..... 150 mV/50 kΩ
- TAPE PLAY1, TAPE2 ..... 150 mV/50 kΩ
- BALANCE IN 1, 2 ..... 150 mV/600 Ω

Output terminals (output level/output impedance)
- TAPE REC 1, 2 ..... 150 mV/1 kΩ
- OUTPUT1 ..... 1 V/0.1 Ω
- OUTPUT2 (BALANCE) ..... 1 V/200 Ω

Maximum output level
- TAPE REC (1 kHz, T.H.D. 0.01%) ..... 12 V
- OUTPUT1 (20 Hz ~ 20 kHz, T.H.D. 0.01%) ..... 5 V
- OUTPUT2 (BALANCE 1 kHz, T.H.D. 0.01%)
  - Load impedance = 600 Ω ..... 3 V
  - Load impedance = 10 kΩ ..... 5 V

PHONO overload level (1 kHz, T.H.D. 0.01%)
- PHONO MM ..... 200 mV

Miscellaneous

Power requirements ..... AC 220 V ~ 230 V, 50/60Hz
Power consumption 70W
External dimensions ..... 460(W) × 158(H) × 446(D)mm
Weight ..... 25.4 kg

Accessories

Operating Instructions 1

The specifications and appearance noted above are subject to change without notice due to improvements.

5. FRONT PANEL FACILITIES



① Power switch(POWER)/indicator

Press to set the power ON/OFF.
When in the ON position,the indicator lights up.No sound will be heard from the speakers for about 6 seconds as a muting circuit is activated to prevent switching noise.

② Function selector switch(FUNCTION)

Use to select program source for playing.

- [CD] ····· To play a compact disc player connected to CD terminal.
- [PHONO] ····· To play a turntable connected to PHONO terminal.
- [TUNER] ····· To play a stereo tuner connected to TUNER terminal.
- [LINE1~LINE5] ····· To play AUDIO equipment connected to LINE terminals.
- [TAPE1/DAT] ····· To play a cassette deck connected to TAPE1/DAT terminal.
- [TAPE2] ····· To play a cassette deck connected to TAPE2 terminal.
- [BALANCE] ····· To play AUDIO equipment connected to BALANCE terminal.

NOTE:
A motor is used to select the function.The function is activated 5 seconds (maximum) after it is selected (e.g. from LINE5 to BALANCE).

③ Volume control(VOLUME)

Use to adjust sound volume.Figures on the dial show the attenuation level when rated output level(1V) is considered to be 0dB.
At the [∞] position, sound will not be heard.

NOTE:
A motor is used to adjust the volume control.
The volume control is activated 2 seconds (maximum) after it is turned (e.g. from ∞ to 0 dB).

④ Balance input selector switch (BALANCE INPUT)

Select either of two balanced inputs.

- 1 ····· To play equipment connected to balance input 1.
- 2 ····· To play equipment connected to balance input 2.

⑤ Recording output on/off selector switch (REC ON/OFF)

- [ON] ····· To output recording signal to terminals of TAPE1/DAT REC,TAPE2 REC, and OUT terminals of LINE4 and LINE5.
- [OFF] ····· To stop output recording signal. When not recording,set the switch to OFF position in order to prevent a connected external terminal from interfering with this terminal, thus ensuring high quality sound.

⑥ Output selector switch (OUTPUT)

Use to select output terminal.

- [OFF] ····· To stop signal output to both output terminals(OUTPUT1,and 2).
- [1] ····· To output a signal to OUTPUT1 terminal(pin-plug) only.
- [2] ····· To output a signal to OUTPUT2 terminal(cannon plug) only.
- [1+2] ····· To output a signal to both output terminals(OUTPUT1 & 2).

⑦ Phase selector switch (ABSOLUTE PHASE)

Use to shift phase both output signals (L and R channels) 180 degrees. When this equipment is used as a component of a system,this feature is helpful to align the phases of appliances connected to this preamplifier.

- 0° ····· Set to this position normally.
- 180° ····· Use when the phases of equipment are not aligned.

CONNECTING BY CANNON PLUG

This appliance is equipped with cannon plugs for two input and one output terminals besides normal pin-jack plugs. When using cannon plugs,connect the balanced output terminal of this equipment to the balanced input terminal of an amplifier(such as an M6) using commercially available cannon plug connecting cords. Using balanced input prevents external noise interference thus enabling high quality sound.

Balance INPUT, OUTPUT



1 GND
2 COLD (−)
3 HOT (+)

NOTE:
When connecting the Cannon plug with the Pioneer EXCLUSIVE M6, adjust the ABSOLUTE PHASE switch to 180°.
(The M6 Balance INPUT is for 1 GND, 2 HOT (+), 3 COLD (−)).

6. SPECIFICATIONS

Amplifier section

Input terminals (sensitivity/impedance)
- PHONO MM ····· 2.5 mV/50 kΩ
- CD ····· 150 mV/50 kΩ
- TUNER ····· 150 mV/50 kΩ
- LINE1, 2, 3, 4, 5 ····· 150 mV/50 kΩ
- TAPE PLAY1, TAPE2 ····· 150 mV/50 kΩ
- BALANCE IN 1, 2 ····· 150 mV/600 Ω

Output terminals (output level/output impedance)
- TAPE REC1, 2 ····· 150 mV/1 kΩ
- OUTPUT1 ····· 1 V/0.1 Ω
- OUTPUT2 (BALANCE) ····· 1 V/200 Ω

Maximum output level
- TAPE REC (1 kHz, T.H.D. 0.01%) ····· 12 V
- OUTPUT1 (20 Hz ~ 20 kHz, T.H.D. 0.01%) ····· 5 V
- OUTPUT2 (BALANCE 1 kHz, T.H.D. 0.01%)
  - Load impedance = 600 Ω ····· 3 V
  - Load impedance = 10 kΩ ····· 5 V

PHONO overload level (1 kHz, T.H.D. 0.01%)
- PHONO MM ····· 200 mV

Miscellaneous

- Power requirements ····· AC 220 V ~ 230 V, 50/60Hz
- Power consumption ····· 70W
- External dimensions ····· 460(W) × 158(H) × 446(D)mm
- Weight ····· 25.4 kg

Accessories

- Operating Instructions ····· 1

The specifications and appearance noted above are subject to change without notice due to improvements.